

UFO Highbay med sensor



3-STEP DIMMING FUNCTION

When used in combination with 1-10V dimmable LED drivers and ballasts, the sensors can achieve 3-step dimming function, 100%---> low light--->off. And the sensors build in adjustable daylight sensors, very easy to install and cost-effective.



With sufficient ambient light, the sensor does not switch on the lamp.

With insufficient ambient light, the sensor switches on the lamp when motion is detected.

After hold time, the sensor dims the lamp at a low light level if no new motion trigger.

After hold time, the sensor dims the lamp at a low light level if no new motion trigger.

After stand-by period, the sensor switches off the lamp if no motion is detected in its detection zone.



Model nummer	LED type	Watt	Volt	Lumen	Ra/cri	Grader på skærm	Garanti	Tæt-hedsgrad	Levetid i timer	Størrelse
HBS-100W-OSH	Nichia	100	185 - 295	15000	>80	120	5år	IP65	50000	Ø400 H176
HBS-150W-OSH	Nichia	150	185 - 295	22500	>80	120	5år	IP65	50000	Ø400 H176